		First Edition	Approved by	Production Div.
	CD Module Specification	June 3, 1998	Checked by	Quality Assurance Div.
	b module specification	Final Revision	Checked by D	Design Engineering Div.

Type No.	DMC - 5 0 1 4 9 N Y U - L Y -	В	Prepared by	Production Div.
<u> </u>				
	Table of	<u>Contents</u>		
	1. General Specifications			
l	2. Electrical Specifications			
	 Optical Specifications I/O Terminal 			
	5. Test			
	6. Appearance Standards			
	 Code System of Production Lot Type Number 			
	9. Applying Precautions			
	10. Handling Precautions			
	Revisio	<u>n History</u>		
Rev.	Date Page 20	heet4	Comment	
DMC	-50149NYU-LY-B (AB) No.98-0118	OPTREX CO	RPORATION	Page 1/16

1. General Specifications

Operating Temp.	: min. 0°C \sim max. 50°C
Storage Temp.	: min20°C \sim max. 70°C
Display Format	: 24 characters \times 2 lines
Display Fonts	: 5 \times 8 dots
Viewing Area	: 93.5 (W) × 15.8 (H) mm
Outline Dimensions	: 121.5 (W) \times 33.5 (H) \times 16.1 max. (D) mm
Weight	: 98g max.
LCD Type	: NTD-7566 (STN / Yellow -mode / Transmissive)
Viewing Angle	: 12:00
Control LSI	: T7934-0100(BR) (Produced by TOSHIBA)
Backlight Additional Spec.	: LED Backlight / Yellow-green : Holder and PWB ground are connected by soldering.
Drawings	: Dimensional Outline UE-33623C

DMC-50149NYU-LY-B (AB) No.98-0118

OPTREX CORPORATION

Page 2/16

2. Electrical Specifications

2.1.Absolute Maximum Ratings

		0			Vss=0V
Parameter	Symbol	Conditions	Min.	Max.	Units
Supply Voltage	Vcc-Vss	_	-0.3	7.0	v
(Logic)					
Supply Voltage	V _{CC} -V _{EE}	—	0	7.0	V
(LCD Drive)					
Input Voltage	VI	_	-0.3	Vcc+0.3	V

2.2.DC Characteristics

Ta=25°C, Vss=0V

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Supply Voltage	Vcc-Vss	—	4.5	—	5.5	V
(Logic)						
Supply Voltage	V _{CC} -V _{EE}		Shown in 3.	1		V
(LCD Drive)						
High Level	VIH	$V_{CC} = 5.0V \pm 10\%$	2.0	—	Vcc	V
Input Voltage		DataSh	oot/		m	
Low Level	VIL	$V_{CC}\!=\!5.0V\!\pm\!10\%$		<u>U_</u> U	0.8	V
Input Voltage						
High Level	Vон	Iон=-1.2mA	2.4	—	Vcc	V
Output Voltage						
Low Level	Vol	IoL=2.0mA	0	—	0.4	V
Output Voltage						
Supply Current	Icc	V _{CC} -V _{SS} =5.0V	_	1.3	2.0	mA



DMC-50149NYU-LY-B (AB) No.98-0118

OPTREX CORPORATION

Page 4/16



2.5.Lighting Specifications

2.5.1.Absolute Maximum Ratings

						Ta=25℃
Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Reverse Voltage	VR	Note 1	_	_	8.0	V
LED Power Dissipation	PD	_	_	_	700	mW

Note 1 : V_F is defined as the voltage between ANODE and CATHODE as shown below.



2.5.2. Operating Characteristics

Ta=25℃

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Units
Foward Current	I_{F}	V _F =5.0V	50	80	100	mA
Luminance of	Ľ.	V _F =5.0V	35			cd/m ²
Backlight Surface	.Dal	aonet	;L4 L	J.CC		

DMC-50149NYU-LY-B	(AB)	No.98-0118
-------------------	------	------------

Page 6/16

3. Optical Specifications

3.1.LCD Driving Voltage

LCD Driving Voltage Note 1 Vcc-Vrtt Ta=25°C 4.4 4.7 5.1 V Note 1 Voc-Vrtt Ta=50°C 4.2 - - V Note 1: Voltage (Applied actual waveform to LCD Module) for the best contrast. The range of minimum and maximum shows tolerance of the operating voltage. The specified contrast ratio and response time are not guaranteed over the entire range. 3.2.Optical Characteristics Ta=25°C, 1/16 Duty, 1/4.5 Bias, Vp=4.7V (Note 4), $\theta = 0^{\circ}$, $\phi = -^{\circ}$ Parameter Symbol Conditions Min. Typ. Max. Units Contrast Ratio Note 1 CR $\theta = 0^{\circ}$, $\phi = -^{\circ}$ $-$ 10 $-$ Viewing Angle Shown in 3.3 Stown in 3.3 Stown in 3.3 Stown in 3.3 Response Rise Note 2 Tow $ 200$ ms Note 1 : Contrast ratio is defined as follows. CR LOF Low Low Low Low Low Low Stown in 3.3	Parameter		Symbol	Conditions	Min.	Тур.	Max.	Units	
Note 1 Ta=50°C 4.2 - - V Note 1: Voltage (Applied actual waveform to LCD Module) for the best contrast. The range of minimum and maximum shows tolerance of the operating voltage. The specified contrast ratio and response time are not guaranteed over the entire range. 3.2.Optical Characteristics Ta=25°C, 1/16 Duty, 1/4.5 Bias, Vp=4.7V (Note 4), $\theta = 0^{\circ}$, $\phi = -^{\circ}$ Optical Characteristics Ta=25°C, 1/16 Duty, 1/4.5 Bias, Vp=4.7V (Note 4), $\theta = 0^{\circ}$, $\phi = -^{\circ}$ Optical Characteristics Ta=25°C, 1/16 Duty, 1/4.5 Bias, Vp=4.7V (Note 4), $\theta = 0^{\circ}$, $\phi = -^{\circ}$ Optical Characteristics Ta=25°C, 1/16 Duty, 1/4.5 Bias, Vp=4.7V (Note 4), $\theta = 0^{\circ}$, $\phi = -^{\circ}$ Optical Characteristics Tota 0° , $\phi = -^{\circ}$ Optical Characteristics Shown in 3.3 Reserved to 0° of 0° , $\phi = -^{\circ}$ Optical Note 2 Contrast ratio is definded as follows. CR = Lorr / Low Low : Luminance of the ON segments Low : Luminance of the ON segments Low : Luminance of the OFF segments <td colspan<="" td=""><td colspan="2">Recommended</td><td></td><td>Ta= 0°C</td><td>_</td><td>—</td><td>5.3</td><td>V</td></td>	<td colspan="2">Recommended</td> <td></td> <td>Ta= 0°C</td> <td>_</td> <td>—</td> <td>5.3</td> <td>V</td>	Recommended			Ta= 0°C	_	—	5.3	V
Note 1 : Voltage (Applied actual waveform to LCD Module) for the best contrast. The range of minimum and maximum shows tolerance of the operating voltage. The specified contrast ratio and response time are not guaranteed over the entire range. 3.2.Optical Characteristics $Ta=25^{\circ}C, 1/16 \text{ Duty}, 1/4.5 \text{ Bias}, V_{D}=4.7V (Note 4), \ \theta = 0^{\circ}, \ \phi = -^{\circ}$ Parameter Symbol Conditions Min. Typ. Max. Units Contrast Ratio Note 1 CR $\theta = 0^{\circ}, \ \phi = -^{\circ}$ — 10 — Viewing Angle Shown in 3.3 Response Rise Note 2 Tow — — — 100 200 ms Time Decay Note 3 Tore — — — 100 200 ms Note 1 : Contrast ratio is defined as follows. CR = Lore / Low Low : Luminance of the ON segments Lore : Luminance of the OFF segments Lore : Luminance of the OFF segments Shown below are applied. Note 3 : The time that the luminance level reaches 90% of the saturation level from 0% when OFF signal is applied. Note 4 : Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1/A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2) / 2 Vth1 : The voltage Vo μ that should provide 50% of the saturation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo μ that should provide 50% of the saturation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo μ that should provide 50% of the saturation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo μ that should provide 50% of the saturation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo μ that should provide 50% of the saturation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo μ that should provide 50% of the saturation level in the luminance at the segment which the OFF signal is applied to.	LCD Dr	iving Voltage	VCC-VEE	Ta=25°C	4.4	4.7	5.1	V	
minimum and maximum shows tolerance of the operating voltage. The specified contrast ratio and response time are not guaranteed over the entire range. 32.Optical Characteristics $\begin{array}{c c c c c c c c c c c c c c c c c c c $		Note 1		Ta=50°C	4.2	_	_	V	
Ta=25°C, 1/16 Duty, 1/4.5 Bias, Vp=4.7V (Note 4). $\theta = 0^{\circ}$, $\phi = -1^{\circ}$ ParameterSymbolConditionsMinTyp.Max.UnitsContrast RatioNote 1CR $\theta = 0^{\circ}$, $\phi = -1^{\circ}$ -10Viewing AngleShown in 3.3ResponseRiseNote 2ToN100200msTimeDecay Note 3ToFF200300msNote 1:Contrast ratio is definded as follows.CR = LOFF / LONLON : Luminance of the ON segments LOFF ? Luminance of the OFF segmentsCOMCOMNote 2:The time that the luminance level reaches 90% of the saturation level from 0% when ON signal is applied.Note 3:The time that the luminance level reaches 90% of the saturation level from 100% when OFF signal is applied.Note 3:The time that the luminance level reaches 10% of the saturation level from 100% when OFF signal is applied.Note 4:Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1 // A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2) / 2Vh1:The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the ON signal is applied to.V0.PUp + Intervent the OFF signal is applied to.V0.PUp + Intervent +	m re	inimum and maxi sponse time are n	mum shows to ot guaranteed o	lerance of the operating					
Contrast Ratio Note 1 CR $\theta = 0^{\circ}$, $\phi = -$ - 10 - Viewing Angle Shown in 3.3 Response Rise Note 2 ToN 100 200 ms Time Decay Note 3 TorF 200 300 ms Note 1: Contrast ratio is defined as follows. CR = LoFF / LON LON : Luminance of the ON segments LOFF : Luminance of the OFF segments COMPACTION Note 2: The time that the luminance level reaches 90% of the saturation level from 0% when ON signal is applied. Note 3: The time that the luminance level reaches 10% of the saturation level from 100% when OFF signal is applied. Note 4: Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1/A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2) / 2 Vth1: The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the ON signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. (B-2) × Vo.P / B				25°C, 1/16 Duty, 1/4.5 B	ias, V _D =4.	7V (Note 4	$\theta = 0^{\circ},$	$\phi = -$	
Viewing Angle Shown in 3.3 Response Rise Note 2 Ton — — — 100 200 ms Time Decay Note 3 Torp — — — — 200 300 ms Note 1: Contrast ratio is definded as follows. CR = Lorr / Lon Lon : Luminance of the ON segments	Pa	rameter	Symbol	Conditions	Min.	Тур.	Max.	Units	
Response Rise Note 2 ToN – – – 100 200 ms Time Decay Note 3 TOFF – – – 200 300 ms Note 1: Contrast ratio is definded as follows. CR = LOFF / LON LON : Luminance of the ON segments LOFF : Luminance of the OFF segments LOFF : Luminance of the OFF segments LOFF : Luminance level reaches 90% of the saturation level from 0% when ON signal is applied. Note 3 : The time that the luminance level reaches 10% of the saturation level from 100% when OFF signal is applied. Note 4 : Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1/A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2) / 2 Vth1 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the ON signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. (B-2) × Vo.P / B	Contrast Rat	io Note 1	CR	$\theta = 0^{\circ}$, $\phi = -^{\circ}$	_	10	—		
Time Decay Note 3 TOFF - - 200 300 ms Note 1 : Contrast ratio is definded as follows. CR = LOFF / LoN LON : Luminance of the ON segments LOFF : Luminance of the OFF segments Decay Mode 3 Toff - - 200 300 ms Note 2 : The time that the luminance level reaches 90% of the saturation level from 0% when ON signal is applied. Note 3 : The time that the luminance level reaches 10% of the saturation level from 100% when OFF signal is applied. Note 4 : Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1/A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2)/2 Vth1 : The voltage VO-P that should provide 50% of the satulation level in the luminance at the segment which the ON signal is applied to. Vth2 : The voltage VO-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage VO-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. VD-P	Viewing Ang	gle			Shown i	n 3.3			
Note 1 : Contrast ratio is definded as follows. CR = LOFF / LON LON : Luminance of the ON segments Sheet4U.com Note 2 : The time that the luminance level reaches 90% of the saturation level from 0% when ON signal is applied. Note 3 : The time that the luminance level reaches 10% of the saturation level from 100% when OFF signal is applied. Note 4 : Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1/A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2) / 2 Vth1 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the ON signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. (B-2) × Vo-P/B	Response	Rise Note 2	Ton	_	_	100	200	ms	
Note 1 : Contrast ratio is definded as follows. CR = LOFF / LON LON : Luminance of the ON segments LOFF : Luminance of the OFF segments Mote 2 : The time that the luminance level reaches 90% of the saturation level from 0% when ON signal is applied. Note 3 : The time that the luminance level reaches 10% of the saturation level from 100% when OFF signal is applied. Note 4 : Definition of Driving Voltage VD Assuming that the typical driving waveforms shown below are applied to the LCD Panel at 1/A Duty - 1/B Bias (A : Duty Number, B : Bias Number). Driving voltage VD is definded as follows. VD = (Vth1+Vth2) / 2 Vth1 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the ON signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vth2 : The voltage Vo-P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. (B-2) × Vo-P/B	Time	Decay Note 3	Toff	_	_	200	300	ms	
the segment which the ON signal is applied to. Vth2 : The voltage Vo.P that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to. Vo.P Vo.P Vo.P (B-2)×VO.P/B	Note 4 : D A 1/	efinition of Drivin ssuming that the A Duty - 1/B Bia follows.	typical driving s (A : Duty N						
Vth2 : The voltage V _{O-P} that should provide 50% of the satulation level in the luminance at the segment which the OFF signal is applied to.	V	-		-	tulation lev	vel in the lu	uminance a	t	
(B-2)×VO-P/B	V	th2 : The voltage	VO-P that shou	ld provide 50% of the sa	tulation le	vel in the lu	iminance a	t	
			×A)		· · ·	(B-2)×V	с-р / В		
VUN SIGNAL/ VUFF SIGNAL/		 ON 	SIGNAL		OFF SIGN	IAL>			

DMC-50149NYU-LY-B (AB) No.98-0118 OPTREX CORPORATION Page 7/16



4.I/O Terminal

4.1.Pin Assignment

No.	Symbol	Level	Function
1	Vss	_	Power Supply (0V)
2	Vcc	—	Power Supply for Logic
3	VEE	—	Power Supply for LCD Drive
4	RS	H/L	Register Select Signal
5	R/W	H/L	Read/Write Select Signal H: Read L: Write
6	Е	H/L	Enable Signal (No pull-up Resister)
7	DB0	H/L	Data Bus Line / Non-connection at 4-bit operation
8	DB1	H/L	Data Bus Line / Non-connection at 4-bit operation
9	DB2	H/L	Data Bus Line / Non-connection at 4-bit operation
10	DB3	H/L	Data Bus Line / Non-connection at 4-bit operation
11	DB4	H/L	Data Bus Line
12	DB5	H/L	Data Bus Line
13	DB6	H/L	Data Bus Line
14	DB7	H/L	Data Bus Line
15	VLED		Power Supply for LED

4.2. Example of Power Supply

It is recommended to apply a potentiometer for the contrast adjust due to the tolerance of the driving voltage and its temperature dependence.





5.<u>Test</u>

No change on display and in operation under the following test condition.

No.	Parameter	Conditions	Notes	
1	High Temperature Operating	$50^{\circ}C \pm 2^{\circ}C$, 96hrs (operation state)		
2	Low Temperature Operating	$0^{\circ}C \pm 2^{\circ}C$, 96hrs (operation state)	3	
3	High Temperature Storage	$70^{\circ}\text{C} \pm 2^{\circ}\text{C}$, 96hrs	4	
4	Low Temperature Storage	$-20^{\circ}\text{C}\pm2^{\circ}\text{C}$, 96hrs		
5	Damp Proof Test	40°C ±2°C, 90~95% RH, 96hrs	3, 4	
6	Vibration Test	Total fixed amplitude : 1.5mm	5	
		Vibration Frequency : $10 \sim 55$ Hz		
		One cycle 60 seconds to 3 directions of X, Y, Z for		
		each 15 minutes		
7	Shock Test	To be measured after dropping from 60cm high on		
		the concrete surface in packing state.		
	www.Dat	F F B A F G B A F G B A F G F G C B F G F G F G G C B G Concrete Surface Face dropping E,F,G face : once Face : once		

Temperature : $20\pm5^{\circ}C$

Humidity $: 65 \pm 5\%$

Note 2 : Unless otherwise specified, tests will be not conducted under functioning state.

Note 3 : No dew condensation to be observed.

Note 4 : The function test shall be conducted after 4 hours storage at the normal temperature and humidity after removed from the test chamber.

Note 5 : Vibration test will be conducted to the product itself without putting it in a container.

DMC-50149NYU-LY-B	(AB)	No.98-0118
-------------------	------	------------

Page 11/16

6. Appearance Standards

6.1.Inspection conditions

The LCD shall be inspected under 40W white fluorescent light.

The distance between the eyes and the sample shall be more than 30cm.

All directions for inspecting the sample should be within 45° against perpendicular line.



6.2. Definition of applicable Zones



A Zone : Active display area

B Zone : Area from outside of "A Zone" to validity viewing area

C Zone : Rest parts

A Zone + B Zone = Validity viewing area

No.	Parameter			Criteria			
1	Black and	(1) Round Shap)e				
	White Spots,		Zone	Ac	ceptable Num	ber	
	Foreign Substances	Dimension (1	nm)	А	В	С	
			$D \leq 0.1$	*	*	*	
		0.1 <	$D \leq 0.2$	5	5	*	
		0.2 <	$D \leq 0.3$	0	1	*	
		0.3 <	D	0	0	*	
		D = (Long	+ Short) / 2	* : Disregar	:d		
		(2) Line Shape					
			Zone	Ac	ceptable Num	ber	
		X(mm)	Y(mm)	А	В	С	
		_	$0.02 \ge W$	*	*	*	
		2.0≧L	0.03≧W	3	3	*	
		1.0≧L	$0.04 \ge W$	1	2	*	
		1.0≧L	$0.05 \ge W$	0	2	*	
		_	$0.05 \! < \! W$	In	the same way	(1)	
		X : Length	Y : Width	* : Disregare	d		
	WWW.	Total defects sh	all not exceed	5.	.com		
2	Air Bubbles						
	(between glass		Zone		Acceptable Number		
	& polarizer)	Dimension (1		А	В	С	
			D ≦0.15	*	*	*	
			$D \leq 0.3$	2	3	*	
			$D \leq 0.5$	1	2	*	
			$D \leq 1.0$	0	1	*	
		* : Disregar	d				
			all not exceed				

No.	Parameter	Criteria
3	The Shape of Dot	(1) Dot Shape (with Dent)
		0.15≧
		As per the sketch of left hand.
		(2) Dot Shape (with Projection)
		Should not be connected to next dot.
		(3) Pin Hole
		$(X+Y)/2 \le 0.2 \text{ mm}$
		(Less than 0.1mm is no counted.)
	WWW.	DataSheet4U.com
		Total defects shall not exceed 5.
4	Polarizer Scratches	Not to be conspicuous defects.
5	Polarizer Dirts	If the stains are removed easily from LCDP surface, the module is not defective.
6	Color Variation	Not to be conspicuous defects.
	1	



10. Handling Precautions

Optrex Products are designed for use in ordinary electronic devices such as business machines, telecommunications equipment, measurement devices and etc..

Optrex Products are not designed, intended, or authorized for use in any application in which the failure of the product could result in a situation where personal injury or death may occur. These applications include, but are not limited to, life-sustaining equipment, nuclear control devices, aerospace equipment, devices related to hazardous or flammable materials, etc. (If Buyer intends to purchase or use the Optrex Products for such unintended or unauthorized applications, Buyer must secure prior written consent to such use by a responsible officer of Optrex Corporation.) Should Buyer purchase or use Optrex Products for any such unintended or unauthorized application (without such consent), Buyer shall indemnify and hold Optrex and its officers, employees, subsidiaries, affiliates and distributors harmless against all claims, costs, damages and expenses, and reasonable attorney's fees, arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Optrex was negligent regarding the design or manufacture of the part.

- 1) LCD may be broken because it is made of glass.
- 2) Polarizer is a soft material and can easily be scratched.
- 3) Please avoid static electricity.
 - ① Please be sure to ground human body and electric appliances during work.
 - ② It is preferable to use conductive mat on table and wear cotton clothes or conduction processed fiber. Synthetic fiber is not recommended.
 - ③ Please slowly peel off protective film, because static electricity may be charged.
- 4) If it is necessary to store LCD modules for a long time, please comply with the following procedures. If storage condition is not satisfactory, display (especially polarizer) may be deteriorated or soldering I/O terminals may become difficult (some oxide is generated at I/O terminals plating).
 - ① Store as delivered by Optrex
 - ⁽²⁾ If you store as unpacked, put in anti-static bag, seal its opening and store where it is not subjected to direct sunshine nor fluorescent lamp.
 - (3) Store at temperature 0 to $+35^{\circ}$ C and at low humidity. Please refer to our specification sheets for storage temperature range and humidity condition.
- The module does not contain excess current limiter.
 Please design the limiter to cut excess current in your power supply circuit.
- 6) Liquid crystal may be leaked when display is broken. Never taste it. If your hands or clothes touch it, please immediately wash using soap.

Optrex shall not be responsible for any infringement of industrial property rights of third parties in any country arising out of the application or use of Optrex Products, except which directly concern the structure or production of such products.