


The 385 relay is a mechanically latched, electrically reset relay. It can be furnished with two, four or six sets of double throw contacts. The molded, plastic dust cover snaps onto a standard DIN rail as well as incorporating mounting slots for panel mounting. The 385 does not have a dominant coil. If both coils are energized at the same time, all of the normally open contacts close and all normally closed contacts open. If one coil, (Coil A) is de-energized, then the contacts on the opposite side (Coil B) will not transition until coil power is restored to the first coil (A).

Contact Characteristics		Units	385
Number and type of Contacts		Oillis	DPDT, 4PDT, 6PDT
Contact materials			Silver Alloy
Thermal (Carrying) Current		Α	15
Maximum Switching Voltage		V	600
Switching Current @ Voltage		➤ Resistive	15A @ 240V 50/60Hz
Swiiching Current & Vollage		Resistive Resistive	10A @ 28V
		ROSISITYC	1/3 @ 120 VAC
Mariana Carinhia Daniana		→ HP	1/2 @ 208 VAC to 600 VAC
Minimum Switching Requirement		mA	100 @ 5 VDC (.5W)
Coil Characteristics			
Voltage Range		• V	12240, 50/60 Hz
		-	12125
Operating Range	% of Nominal	•	85% to 110%
	:	=	80% to 110%
Average consumption	•	~ ∨A	2
•		- W	1.64
Drop-out voltage threshold	•	•	15%
,		-	10%
Performance Characteristics			
Electrical Life (UL508)	Operations @ Rated Current	(Resistive)	100.000
Mechanical Life	<u> </u>	,	10,000,000
Operating time (response time)	Unpowered	ms	25
Dielectric strength	Between coil and contact	➤ V(rms)	2000
O	Between poles	► V(rms)	1500
	_	V(rms)	1500
Environment		. , ,	
Product certifications	Standard version		UL
Ambient air temperature	Storage	°C	-40+85
around the device	Operation	°C.	-40+55
Vibration resistance	Operational	g-n	3, 10 - 55 Hz
Shock resistance	- 1	g-n	10
Degree of protection		9-11	IP 40
Weight		grams	85





w DataSheet4U.com

Standard Part Numbers

BOLD-FACED PART NUMBERS ARE NORMALLY STOCKED

Nominal Voltage	Coil Resistance	Part Number Part Number		Part Number
AC Operated (Single Coil)		DPDT	4PDT	6PDT
12 VAC 50/60 HZ	30/30 Ohms	385XBX-12A	385XDX-12A	385XFX-12A
24 VAC 50/60 HZ	180/180 Ohms	385XBX-24A	385XDX-24A	385XFX-24A
120 VAC 50/60 HZ	3,800/3,800 Ohms	385XBX-120A	385XDX-120A	385XFX-120A
240 VAC 50/60 HZ	16,000/16,000 Ohms	385XBX-240A	385XDX-240A	385XFX-240A
DC Operated				
12 VDC	85/85 Ohms	385XBX-12D	385XDX-12D	385XFX-12D
24 VDC	340/340 Ohms	385XBX-24D	385XDX-24D	385XFX-24D
48 VDC	1,360/1,360 Ohms	385XBX-48D	385XDX-48D	385XFX-48D
110-125 VDC	9,000/9,000 Ohms	385XBX-110/125D	385XDX-110/125D	385XFX-110/125D

Part Number Builder

	i di i i tomber bonder				
ľ	F	385	XBX	-	240A
ı	Temperature Class	Series	Contact Configuration		Coil Voltage
	130° C = None	385	DPDT = XBX		VAC = 6 - 240A
	155° C = F		4PDT = XDX		VDC = 6 - 125D
			6PDT = XFX		

